

- > Port size: G1/4 and NAMUR interface
- > For single and double operated actuators
- Standard manual override with detent
- Simple design of soft spool seal system
- Compact design, high flow rate

- Easily interchangeable solenoid system
- > Maintenance-free
- Valves and solenoids are ATEX approved (see table)









# **Technical features**

#### Medium:

Compressed air, filtered, lubricated or non-lubricated

#### Operation:

Solenoid, indirectly controlled

#### Operating pressure:

2 ... 8 bar (29 ... 116 psi)

#### Orifize:

6 mm

#### Port size:

G 1/4

NAMUR Interface with integrated exhaust air

#### Mounting position:

Optional, preferably with solenoid on top

#### Flow direction:

Fixed

### **Electrical connection:**

See solenoid table

### Ambient/Media temperature:

-10° ... +50°C (+14° ... +122°F) Solenoid: see solenoid table Air supply must be dry enough to avoid ice formation at temperatures below 2°C (+35°F).

#### Materials:

Housing: Aluminium Pilot flange: Plastic Seat seal: NBR

### **Technical data**

2 3 G 1/4 Flange Solenoi				(kg)	No.	*1)
The state of the s	id indirectly controlled 6	2 8	1,2	0,4	1	8010777
	id indirectly controlled 6	2 8	1,2	0,55	2	2623077
G 1/4 Flange Solenoi	id indirectly controlled 6	2 8	1,2	0,9	3	2623177

## 3/2 or 5/2 way function (conversion instruction see page 6)

Symbol	Ports 1, 3 (5)	2 (4)	Actuation	Nominal size	Operating pressure (bar)	kv-value (Cv (US) ≈ kv x 1,2)	Weight (kg)	Dimension No.	Model *1)
2 3	G 1/4	Flange	Solenoid indirectly controlled	6	2 8	1,2	0,4	4	2623079
1 3									
4 2	G 1/4	Flange	Solenoid indirectly controlled	6	2 8	1,2	0,9	5	2623179
513									

<sup>\*1)</sup> When ordering please indicate solenoid, voltage and current type (frequency).





### **Solenoid actuators**

	Power	otion	Rated cu	rrent	Protection class	Ex-Protection (ATEX-Category)	Temperature Ambient/	Electrical connection	Weight	Drawing	Circuit diagram	Model
		230 V a.c. (VA)	24 V d.c. (m A)	230 V a.c. (m A)	IP/NEMA		Media (°C)		(kg)	No.	No.	
	1,8	_	70	_	IP65 (with connector)	-	-15 +50	Connector DIN EN 175301-803, form B *1)	0,1	11	1	3050
	1,6	_	30	_	IP65 (with connector)	_	-15 +50	Connector DIN EN 175301-803, form A *1)	0,1	12	1	3036
1	2,7	_	115	_	IP65 (with connector)	II 2 G Ex mb IIC T5 Gb II 2 D Ex mb tb T95°C Db	-20 +50 *2)	Cable length 3 m	0,3	13	14	3062
Service Service	_	2,1	-	9	IP65 (with connector)	II 2 G Ex mb IIC T5 Gb II 2 D Ex mb tb T95°C Db	-20 +50 *2)	Cable length 3 m	0,3	13	15	3063
(a)	2,7	_	115	_	IP66 (with connector)	_	-10 +50	Connector *1) M12x1, DIN IEC 61076-2-101 Solenoid with yellow LED	0,1	14	17	3071

Standard voltages (±10%) 24 V d.c., 230 V a.c., other voltages on request.

# **Approvals**

Model	Approvals ATEX	IECEx	FM	Datasheet
306x	PTB 03 ATEX 2015	_	_	N/en 7.1.560
307x	EC-Declaration of Conformity	_	_	N/en 7.1.565

### **Accessories**


Connector Form A	M12 x 1		Silencer	Flange plate	Yoke
			Page 7	Page 7	Page 7
0570275 (form A)	0523055 (without cable)	0523056 (90°, wi hout cable)	M/S2 G1/4	0612790 (NAMUR single connection plate)	0540593
0680003 (form B)	0523057 (2 m cable)	0523058 (90°, 2 m cable length)		0612791 (NAMUR-rip use in combination wi h 0612790, Alu)	
	0523052 (5 m cable)	0523053 (90°, 5 m cable length)			

<sup>\*1)</sup> Connector is not scope of delivery, see table »Accessories«


36

# Dimensions Valves






2




Dimensions in mm Projection/First angle







- 1 Solenoid 90° turnable
- 2 Manual override with detent
- 3 NAMUR centering hole




ø15,5

ø19,5

32


55





37






55

Dimensions in mm Projection/First angle









- 1 Solenoid 90° turnable
- 2 Manual override with detent
- 3 NAMUR centering hole

Dimensions in mm Projection/First angle


 $\bigcirc$ 





## **Dimensions**

# **Solenoid operators**











1 Connector 4 x 90° turnable

# 12







## Electrical connection M 12 x 1





Pin	Signal	Cable
1	+ UB	brown
2	Out 2 (PNP) / analogue 4 to 20 mA	white
3	0 Volt	blue
4	Out 1 (PNP)	black

# Circuit diagrams












# NAMUR hole pattern (driving side)





Dimensions in mm



2 Port 2 (A)

3 Coding stud threaded

4 M5 (10 deep)


5 Port 3 (R)

NAMUR quick exhaust module for a better kv-value by exhaust see data sheet 5.4.820

NAMUR interlinking plates in redundancy design for »safety exhausting« and »safety ventilating« see data sheet 5.4.830


# **Conversion instructions of** 5/2 into 3/2 way function

# 5/2 way function (original mode of supply)



3/2 resp. 5/2 way function can be achieved just by swapping enclosed adaptor plates. Make sure Marker and Arrow do match as shown on above drawing. Original mode of supply: 5/2 function.


# 3/2 way function





6 Arrow

7 Marker

# Single connection plate Model: 0612790









# **NAMUR** slot Model: 0612791

Dimensions in mm Projection/First angle










# Yoke Model: 0540593



# Silencer Model: M/S2



### Warning

These products are intended for use in industrial compressed air systems only. Do not use these products where pressures and temperatures can exceed those listed under

# »Technical features/data«.

Before using these products with fluids other than those specified, for non-industrial applications, life-support systems or other applications not within published specifications, consult IMI NORGREN.

Through misuse, age, or malfunction, components used in fluid power systems can fail in various modes.

The system designer is warned to consider the failure modes of all component parts used in fluid power systems and to provide adequate safeguards to prevent personal injury or damage to equipment in the event of such failure.

System designers must provide a warning to end users in the system instructional manual if protection against a failure mode cannot be adequately provided.

System designers and end users are cautioned to review specific warnings found in instruction sheets packed and shipped with these products.